


## INSTRUCTION MANUAL


### 2 Gang Zigbee Push button/Normal Switch Module

QS-Zigbee-SEC02




## TECHNICAL SPECIFICATIONS

Product type	2 Gang Zigbee Push button/Normal Switch Module
Voltage	100-240V AC 50/60Hz
Current	2x5A
Max. load	2x1150W/2x250W for LED
Operation frequency	2.4GHz-2.484GHz IEEE 802.15.4
Operation temp.	-10°C - +40°C
Operation range	≤ 200 m
Dims (WxDxH)	39x39x18 mm
IP rating	IP20
Warranty	2 years
Certificates	CE, ROHS




Global international operation Whenever & Wherever  
You are, All-in-one Mobile App



## INSTALLATION

### Warnings:

1. Installation must be carried out by a qualified electrician in accordance with local regulations.
2. Keep the device out of reach of children.
3. Keep the device away from water, damp or hot environment.
4. Install the device away from strong signal sources such as microwave oven that may cause signal interruption resulted to abnormal operation of the device.
5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.
6. Do NOT attempt to disassemble, repair or modify the device.




## MANUAL OVERRIDE

The switch module terminal reserves the access of manual override function for the end-user to switch on/off.

\* Switch on/off for permanent on/off function.

### Notes:

- 1) Both the adjustment on App and switch can override each other, the last adjustment remains in memory.
- 2) The App control is synchronized with the manual switch.




2



Log in or register your account with your mobile number or e-mail address. Type in the verification code sent to your mobile or mail box, then set your login password. Click "Create Family" to enter into the APP.


3



Open the control panel of the ZigBee gateway on the App

Before making the reset operation, pls make sure the Zigbee Gateway is added and installed to the WIFI network. Ensure that the product is within the range of Zigbee Gateway Network.

4





Turn on/off the manual switch for five times or long press the reset key for about 10seconds until the indicator light on the module flash quickly for pairing.(If you wait more than 180 seconds you need to repeat this passage)

5




Click "+" (Add sub-device) to select the suitable product gateway and follow the on-screen instruction for pairing.

6




The pairing usually will be finished soon. Pls make your mobile phone and device as close as possible.

7




When pairing is done, the Wi-Fi switch will be shown on the App.

8



Connect to amazon alexa or Google Assistant for voice control, or share the devices with your families or friends.

9



#### SYSTEM REQUIREMENTS

- WIFI Router
- ZigBee gateway
- iPhone, iPad (iOS 7.0 or higher)
- Android 4.0 or higher